

Emergency Door Release Button



RESETKEY-N



Red light shows when button has been activated and needs resetting



White light displays when button not in use

SPECIFICATION

- Single pole
- 1 x Pole (Positive switching)
- Double pole
- 1 x Pole (Positive switching)
- 1 x Pole (Changeover contact)
- Triple pole (
- 1 x Pole (Positive switching)
- 2 x Pole (Changeover contact)
- Includes audible/LED (selectable)
- 12/24V operation
- Voltage 12/24 VDC @ 30/45mA
- Operating temperature: -10C to 55C
- IP24 Rated
- Resettable

FEATURES

- All one colour
- Easy clean surface (ideal for hospitality areas)
- Easy cable entry from sides or rear
- Screw footprint for surface fitting onto standard back box
- Key reset operation (not replacement glass)
- Internal use
- Emergency Door Release - permanently lit.
- Changes to red on activation/alarm
- Includes plastic front covers which flip up for operation

DIMENSIONS

- 87x87x60 (mm)
- 248g (Boxed)
- 162g (Unboxed)

CONTENTS

- Emergency Door Release
- Security Screws
- Allen Key
- Mounting Plate
- 2 RESETKEY-N